



BEAMZ
MADE
EAZY

150.706 V1.2

LCB144 MKII

QUICK **START GUIDE**

DMX CHANNELS

3 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	COLOR	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%

4 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	COLOR	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	MASTER DIMMER	000-255	Master dimmer 0-100%

7 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	COLOR	000-255	Red dimmer 0-100%
2		000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	MASTER DIMMER	000-255	Master dimmer 0-100%
5	STROBE	000-255	Strobe speed
6	CHASE	000-025	Chase mode 0 (chase 1-8 cycle running)
		026-051	Chase mode 1
		052-077	Chase mode 2
		078-103	Chase mode 3
		104-129	Chase mode 4
		130-155	Chase mode 5
		156-181	Chase mode 6
		182-207	Chase mode 7
		208-233	Chase mode 8
		234-255	Chase mode 9
7	MODE	000	Dimmer mode (custom control)
		001-013	Chase mode (Selection by channel 6)
		014-027	Sound mode A0 (all mode A cycle running)
		028-139	Sound mode A1-A8 alone
		140-153	Sound mode B0 (all mode B cycle running)
		154-255	Sound mode B1-B8 alone

24 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	SECTION 1	000-255	Red dimmer 0-100%
2	COLOR	000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	SECTION 2	000-255	Red dimmer 0-100%
5	COLOR	000-255	Green dimmer 0-100%
6		000-255	Blue dimmer 0-100%
7	SECTION 3	000-255	Red dimmer 0-100%
8	COLOR	000-255	Green dimmer 0-100%
9		000-255	Blue dimmer 0-100%
10	SECTION 4	000-255	Red dimmer 0-100%
11	COLOR	000-255	Green dimmer 0-100%
12		000-255	Blue dimmer 0-100%
13	SECTION 5	000-255	Red dimmer 0-100%
14	COLOR	000-255	Green dimmer 0-100%
15		000-255	Blue dimmer 0-100%
16	SECTION 6	000-255	Red dimmer 0-100%
17	COLOR	000-255	Green dimmer 0-100%
18		000-255	Blue dimmer 0-100%
19	SECTION 7	000-255	Red dimmer 0-100%
20	COLOR	000-255	Green dimmer 0-100%
21		000-255	Blue dimmer 0-100%
22	SECTION 8	000-255	Red dimmer 0-100%
23	COLOR	000-255	Green dimmer 0-100%
24		000-255	Blue dimmer 0-100%

28 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	SECTION 1	000-255	Red dimmer 0-100%
2	COLOR	000-255	Green dimmer 0-100%
3		000-255	Blue dimmer 0-100%
4	SECTION 2	000-255	Red dimmer 0-100%
5	COLOR	000-255	Green dimmer 0-100%
6		000-255	Blue dimmer 0-100%
7	SECTION 3	000-255	Red dimmer 0-100%
8	COLOR	000-255	Green dimmer 0-100%
9		000-255	Blue dimmer 0-100%
10	SECTION 4	000-255	Red dimmer 0-100%
11	COLOR	000-255	Green dimmer 0-100%
12		000-255	Blue dimmer 0-100%
13	SECTION 5	000-255	Red dimmer 0-100%
14	COLOR	000-255	Green dimmer 0-100%
15		000-255	Blue dimmer 0-100%
16	SECTION 6	000-255	Red dimmer 0-100%
17	COLOR	000-255	Green dimmer 0-100%
18		000-255	Blue dimmer 0-100%
19	SECTION 7	000-255	Red dimmer 0-100%
20	COLOR	000-255	Green dimmer 0-100%
21		000-255	Blue dimmer 0-100%
22	SECTION 8	000-255	Red dimmer 0-100%
23	COLOR	000-255	Green dimmer 0-100%
24		000-255	Blue dimmer 0-100%
25	MASTER DIMMER	000-255	Master dimmer 0-100%
26	STROBE	000-255	Strobe speed
27	CHASE	000-025	Chase mode 0 (chase 1-8 cycle running)
		026-051	Chase mode 1
		052-077	Chase mode 2
		078-103	Chase mode 3
		104-129	Chase mode 4
		130-155	Chase mode 5
		156-181	Chase mode 6
		182-207	Chase mode 7
		208-233	Chase mode 8
		234-255	Chase mode 9
28	MODE	000	Dimmer mode (custom control)
		001-013	Chase mode (Selection by channel 6)
		014-027	Sound mode A0 (all mode A cycle running)
		028-139	Sound mode A1-A8 alone
		140-153	Sound mode B0 (all mode B cycle running)
		154-255	Sound mode B1-B8 alone



A series of horizontal dotted lines for writing, spanning the width of the page.



A series of horizontal dotted lines for writing, spanning the width of the page.





A series of horizontal dotted lines spanning the width of the page, intended for writing.



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

