



1150.443 V1.0

PANTHER8ØL QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION	
Addr	A000-A512	DMX address setting	
Chnd	16CH	Channel	
SLnd	SLAU	DMX	
Shnd	Auto	Auto mode	
	Sound	Sound mode	
	SH0	Auto mode 1	
	SH1	Auto mode 2	
	SH2	Auto mode 3	
	SH3	Auto mode 4	
Sens	0-99	Sound sensitivity adjustment	
Led	OFF	Display turns off after 10 seconds	
	ON	Always on	
disp	NO	Display reverse	
	YES	Display normal	
rPAN	YES	X motor reverse	
	NO	X motor forward	
rEiL	YES	X motor reverse	
	NO	X motor forward	
lr	ON	Remote control ON	
	OFF	Remote control OFF	
LOAd		Factory setting	
rEST		Reset	

REMOTE CONTROL



ON	Lights on	
OFF	Lights off	
DMX	DMX mode	
AUT0	Self-walking	
speed+	Control the speed fast	
speed-	Control the speed slow	
voice	Voice control	
mic+	Sound sensitivity +	
mic-	Sound sensitivity-	
1	LED red wash	
2	LED green wash	
3	LED blue wash	
4	LED white wash	
5	Green Laser	
6	LED red+green	
7	LED red+ blue	
8	LED green+blue	
9	LED red+ white	
0	LED all colors on	
*	Auto mode for Z motor	
#	Save setting	

DMX CHANNELS

16 CHANNELS	FUNCTION	VALUE	DESCRIPTION	
1	PAN	000-255	Movement 0°-540°	
2	PAN FINE	000-255	Movement 0°-540°	
3	TILT	000-255	Movement 0°-270°	
4	TILT	000-255	Movement 0°-270°	
5	SPEED	000-255	Pan /Tilt speed from fast to slow	
6	MASTER DIMMER	000-255	Master Dimmer 0-100%	
7	STROBE	000-009	No Function	
		010-249	Strobe from slow to fast	
		250-255	No Function	
8	RED	000-255	Dimmer Red 0-100%	
9	GREEN	000-255	Dimmer Green 0-100%	
10	BLUE	000-255	Dimmer Blue 0-100%	
11	WHITE	000-255	Dimmer White 0-100%	
12	Z MOTOR	000-255	0-100%	
13	LASER	000-255	Dimmer Laser 0-100%	
14	MACR0	000-029	No Function	
		030-149	Auto program	
		150-255	Sound mode	
15	SPEED	000-255	Speed from fast to slow (CH14)	
16	MODE	000-020	No Function	
		021-100	X Axis Final motion	
		101-200	Y Axis Final motion	
		201-249	X Y Axis Final motion	
		250-255	Reset (Holds for 5 seconds)	

YOUR FUTURE YOUR SKILLS YOUR PLATFORM YOUR PARTY YOUR EUENT

≥beamZ

is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.