

# BLUETOOTH WALL PLAYER

pearl  
one more better



Optional Speaker:  
Coaxial Ceiling Speaker



HSR175-5C



HSR108-5C


## Description

Small amplifier for background music system,output power reach 15W max@8 ohms low impedance output,has a 34x37mm display screen,it is suitable for office,restaurant,shop.etc.

## Features

- 1, USB,SD can play mp3 music files.
- 2, FM radio,support frequency from 88MHz to 108MHz.
- 3, Bluetooth,support smartphone/computer.
- 4, 3.5mm audio jack,support analog audio input.
- 5, IR remote control to control all operations.


### Panel Instruction:




- 1.EQ select
- 2.Short press: PRE song  
Long press: VOL-
- 3.Screen
- 4.Power switch
- 5.3.5mm AUX input
- 6.Short press: Play/Pause  
Long press:FM search
- 7.Model switch:  
USB-SD-FM-AUX-Bluetooth  
Long press:sleep mode
- 8.Short press: Next song  
Long press: VOL+
- 9.USB port
- 10.SD card port
- 11.IR receiver



### USB/SD position



### Power switch/AUX jack position



Specification\Model	HYC1215
Output Power	15W Stereo
Input Functions	USB,SD,FM,Bluetooth,AUX
Frequency Response	20~20KHz
Output Interface	8-Ohms,8Ω,Stereo(left and right)
Power Supply	AC110/220V(built-in transformer), or 9~15VDC (use a DC adapter)
Dimensions:WxHxD	73x116x60